



Testing intervals extract from AS3760:2010

Type of environment and/or equipment	Interval between inspection and tests				
	Equipment including Class 1, Class II, cord sets, cord extension sets and EPODs	Residual current devices (RCDs)			
		Push-button test - by user		Operation time and push-button test	
		Portable	Fixed	Portable	Fixed
1. Factories, workshop, places of manufacture, assembly, maintenance or fabrication.	6 months	Daily, or before every use, whichever is longer	6 months	12 months	12 months
2. Environment where the equipment or supply flexible cord is subject to flexing in normal use OR is open to abuse OR is in a hostile environment	12 months	3 months	6 months	12 months	12 months
3. Environment where the equipment or supply cord is NOT subject to flexing in normal use and is NOT open to abuse and is NOT in a hostile environment	5 years	3 months	6 months	2 years	2 years
4. Residential type areas of: hotels, residential institutions, motels, boarding houses, halls, hostels accommodation houses, and the like	2 years	6 months	6 months	2 years	2 years
5. Equipment used for commercial cleaning	6 months	Daily, or before every use, whichever is longer	N/A	6 months	N/A
6. Hire equipment: Inspection Test and Tag	Prior to hire	Including push-button test by hirer prior to hire N/A		N/A	N/A
	3 months	N/A		3 months	12 months
7. Repaired, serviced and second hand equipment	After repair or service which could affect electrical safety, or on reintroduction to service, <i>refer to AS/NZS 5762.</i>				